

# RT 45/G



The SHEV operation panel is used to trigger and reset SHEV systems. Additional display elements for operational standby, alarms and faults are available.

## Performance features

- + For 24 V DC D+H smoke vent control panels
- + Can be used as main or auxiliary control panel
- + For manually triggering a SHEV system in case of fire
- + Function: SHEV OPEN, SHEV Reset
- + Display: Operational standby, alarm triggered and fault
- + Integrated ventilation button, optional
- + Available in 5 powder-coated colours

# Approvals / Certificates

Find out about permission details from your D+H Partner.



G 510003

Article also available with the following permissions under other article numbers. Technical data may deviate.



CNBOP-PIB

# Technical data

## RT 45/G

Input voltage	18 ... 28 V DC
Type of protection	IP 40
Temperature range	-5 °C ... +40 °C
Housing	Die-cast aluminium
Colour	Grey (~ RAL 7035)
W x H x D	129 x 138 x 39 mm
Weight	0.31 kg
Remark	Complete SHEV operation panel
Art. No.	65.403.24

# Example of application

