

RT 45



The SHEV operation panel is used to trigger and reset SHEV systems. Additional display elements for operational standby, alarms and faults are available.

Performance features

- + For 24 V DC D+H smoke vent control panels
- + Can be used as main or auxiliary control panel
- + For manually triggering a SHEV system in case of fire
- + Function: SHEV OPEN, SHEV Reset
- + Display: Operational standby, alarm triggered and fault
- + Integrated ventilation button, optional
- + Available in 5 powder-coated colours

Approvals / Certificates

Find out about permission details from your D+H Partner.



G 510003

Article also available with the following permissions under other article numbers. Technical data may deviate.



CNBOP-PIB

Technical data

RT 45

| | |
|--------------------|-------------------------------|
| Input voltage | 18 ... 28 V DC |
| Type of protection | IP 40 |
| Temperature range | -5 °C ... +40 °C |
| Housing | Die-cast aluminium |
| Colour | Orange (~ RAL 2011) |
| W x H x D | 129 x 138 x 39 mm |
| Weight | 0.31 kg |
| Remark | Complete SHEV operation panel |
| Art. No. | 65.403.23 |

Example of application

