

# RT 45/G



The SHEV operation panel is used to trigger and reset SHEV systems. Additional display elements for operational standby, alarms and faults are available.

## Performance features

- + For 24 V DC D+H smoke vent control panels
- + Can be used as main or auxiliary control panel
- + For manually triggering a SHEV system in case of fire
- + Function: SHEV OPEN, SHEV Reset
- + Display: Operational standby, alarm triggered and fault
- + Integrated ventilation button, optional
- + Available in 5 powder-coated colours

# Approvals / Certificates

Find out about permission details from your D+H Partner.



G 510003

Article also available with the following permissions under other article numbers. Technical data may deviate.



CNBOP-PIB

# Technical data

## RT 45/G

|                    |                               |
|--------------------|-------------------------------|
| Input voltage      | 18 ... 28 V DC                |
| Type of protection | IP 40                         |
| Temperature range  | -5 °C ... +40 °C              |
| Housing            | Die-cast aluminium            |
| Colour             | Grey (~ RAL 7035)             |
| W x H x D          | 129 x 138 x 39 mm             |
| Weight             | 0.31 kg                       |
| Remark             | Complete SHEV operation panel |
| Art. No.           | 65.403.24                     |

# Example of application

